A40

STEREO AMPLIFIER WITH BT, 60W

- 8Ω Minimum Impedance
- Discreet Design
- Extended Compatibility
- AUX Input
- Space Saving
- Ultra-Thin Design

The A40 is a 60W amplifier with an ultra small size and weight to integrate in your small and medium installations allowing you to install it where it is most convenient for you. It can be installed on a wall, ceiling or furniture for space saving keeping the space decor. Take advantage of the BT connection, sonorizing your space easily. You can use your A40 down to 8Ω minimum impedance.

Product Type
BT Class D Amplifier

Frequency Response (-6dB)
20Hz - 20kHz

Amplifier Technology
Class D Amplifier

Amplifier Power
2 x 30W@8Ω

Speaker Output
8Ω - 16Ω

THD+N
<0.1%

SNR (Signal to Noise Ratio)
>82dB

Input Sensitivity
0dBV (0.7V)

Wireless Connection System
BT v2.1 + EDR

Wireless Range
10m (32.8ft)

Audio Signal Inputs
BT | Stereo Line-in

Input Connectors
3.5mm Stereo Jack

Cooling Type
Convection

Power Input
AC 100V-240V / 50Hz-60Hz

Power Consumption
0.24W - Idle

Construction
Aluminum

IP Rating
Indoor Use

Dimensions (WxHxD)
100 x 35 x 125mm (3.9" x 1.4" x 4.9")

Fixation
Screw Fixation to Wall / Ceiling

Net Weight
330g (0.73lb)

Shipping Weight
350g (0.77lb)